



## Digital Audio Booster AES-B-20

**AES-B-20 is a portable and compact Digital Audio Level Booster. It offers selectable gain of +12 and +24 dB. An overrange indicator will help finding the right setting.**

AES-B-20 is a very compact, battery-powered digital audio level booster, housed in an black-anodized all aluminium case.

Inputs and outputs are 3-pole XLRs, for AES digital signals only.

Gain is selectable in three steps: 0 dB, +12 dB and +24 dB.

An overrange indicator show red at 0 dBFS.

The unit works entirely in the digital domain.

AES-B-20 can be powered by four internal standard AAA batteries for 10 - 15 hours continuous use, or by an external DC power supply with 6 - 18 V output @ 100 mA.

- Booster for digital audio
- Selectable gain 0/+12/+24 dB
- XLR in/out for AES
- Overrange indicator
- Heavy-duty metal case
- Compact size
- 4 x AAA batteries
- External DC 6-18 V

### Technical Data

Gain select	0 / +12 / +24 dB
Audio i/f	AES
Audio formats	16-24 bits @ 32 - 96 kHz
Power supply	4 x AAA alkaline or NiMH batteries for 10 -15 hours continuous use Ext. DC 6 - 18 V
Size WxHxD	90 x 40 x 135 mm
Weight	520 grams (incl. batteries)

Specifications are subject to change without notice.

